



## Husqvarna CFD 67

Husqvarna CFD is a diesel driven generator with one to four outlets for powering AX and Vibrastar 42 Volt/200 Hz high-frequency electric concrete vibrators anywhere. The generator is motorized by a Lombardini diesel engine and features side covers and a solid frame for transport wheels.

### Easy to stop

The stop switch is conveniently located on the main panel, making it to easy to locate and reach.

### Voltage control

To prevent overvoltage, the generator is equipped with a voltmeter and kill ignition controls.

### Reliable operation

The generator is motorized with a rubber-mounted Lombardini diesel engine.

### Run up to four vibrators at the same time

To help you get the job done quickly and efficiently, the generator features up to four outlets so you can run a maximum of four vibrators simultaneously.

## FEATURES

- Reliable operation
- Voltage control
- Easy to stop
- Run up to four vibrators at the same time

### Technical Specifications

#### ENGINE

Output power	5.4 kW
Exhaust emissions (CO2 EU V)	976 g/kWh

#### SPECIFICATIONS

Rated current	65 A
Frequency	200 Hz
Wheels	Yes

#### DIMENSIONS

Weight	95 kg
--------	-------

#### SOUND AND NOISE

Sound level	107 dB(A)
-------------	-----------

#### PACKAGING

Packaging length	610 mm
Packaging width	850 mm
Packaging height	850 mm