



Husqvarna CFG 67

Husqvarna CFG is a petrol-powered generator with one to four outlets for powering AX and Vibrastar 42 Volt/200 Hz high-frequency electric concrete vibrators anywhere. The generator is motorised by a Honda petrol engine and features side covers and a solid frame for transport wheels.

Easy to stop

The stop switch is conveniently located on the main panel, making it to easy to locate and reach.

Voltage control

To prevent overvoltage, the generator is equipped with a voltmeter and kill ignition controls.

Reliable operation

The generator is driven by a Honda petrol engine mounted on vibration dampening rubber.

Run up to four vibrators at the same time

To help you get the job done quickly and efficiently, the generator features up to four outlets so you can run a maximum of four vibrators simultaneously.

FEATURES

- Reliable operation
- Voltage control
- Easy to stop
- Run up to four vibrators at the same time

Technical Specifications	
ENGINE	
Output power	6.3 kW
Exhaust emissions (CO2 EU V)	762 g/kWh
SPECIFICATIONS	
Rated current	67 A
Frequency	200 Hz
Wheels	Yes
DIMENSIONS	
Weight	85 kg
SOUND AND NOISE	
Sound level	96 dB(A)
PACKAGING	
Packaging length	610 mm
Packaging width	850 mm
Packaging height	850 mm
Packaging volume	441 dm ³