



Husqvarna CFG 25

Husqvarna CFG is a petrol-powered generator with one to four outlets for powering AX and Vibrastar 42 Volt/200 Hz high-frequency electric concrete vibrators anywhere. The generator is motorized by a Honda petrol engine and features side covers and a solid frame for transport wheels.

Easy to stop

The stop switch is conveniently located on the main panel, making it to easy to locate and reach.

Voltage control

To prevent overvoltage, the generator is equipped with a voltmeter and kill ignition controls.

Reliable operation

The generator is driven by a Honda petrol engine mounted on vibration dampening rubber.

FEATURES

- Reliable operation
- Voltage control
- Easy to stop

| Technical Specifications | |
|------------------------------|---------------------|
| ENGINE | |
| Output power | 3.6 kW |
| Exhaust emissions (CO2 EU V) | 757 g/kWh |
| SPECIFICATIONS | |
| Rated current | 25 A |
| Frequency | 200 Hz |
| Wheels | Optional |
| DIMENSIONS | |
| Weight | 45 kg |
| SOUND AND NOISE | |
| Sound level | 93 dB(A) |
| PACKAGING | |
| Packaging length | 610 mm |
| Packaging width | 850 mm |
| Packaging height | 850 mm |
| Packaging volume | 441 dm ³ |